

NEW PRODUCT DATA SHEET

PAGlink PowerHub

MORE OUTPUTS FOR CAMERA ACCESSORIES



- Power 12V camera accessories from PAGlink Gold Mount batteries.
- Sandwich PowerHub between batteries to maintain hot-swap capability.
- Keep accessories plugged-in and powered-up when changing batteries.
- Includes 4 x D-Tap outputs for 12V camera accessories.
- Includes a USB output for 5V accessories or charging your smartphone.
- Interchangeable Lemo and Hirose connectors available separately.

DESCRIPTION

The PowerHub is a compact and user-configurable camera accessory power device, designed for use with the PAGlink Gold Mount system of intelligent linking batteries.

The PAGlink battery system is designed for high-load camera set-ups; the linked batteries provide up to 12A, enabling you to power simultaneously the camera and multiple 12V accessories, such as a camera light, a monitor, audio and transmission devices. The PowerHub provides the multiple outputs that are required to do this.

PowerHub incorporates five output ports that accept a range of interchangeable, plug-in connectors. Four D-Tap connectors are supplied as standard; a USB connector (5V, 1A) is also included which allows you to charge your smartphone, or power similar low-voltage devices. These connectors are interchangeable with Lemo (2-pin), Hirose (4 pin) or 2.1mm (PP90) connectors, available in addition, and can be used in any of the 5 ports. Any combination of connectors is possible enabling you to configure the PowerHub to your exact requirement.

The ultra-compact and lightweight PowerHub is designed to be used sandwiched between two PAGlink batteries, increasing the depth of the battery stack by just 12mm. This enables the rear battery to be hot-swapped without disconnecting the accessories. This is not true when accessories are plugged into the built-in D-Tap found on some other manufacturer's batteries. Alternatively, the PowerHub can be connected to rear battery of the stack.

The PowerHub Model 9712 can only be used with PAGlink Gold Mount batteries (Models 9306 and 9313). It draws power from the PAGlink contacts on the face of the battery. It cannot be connected directly to the camera or used with non-linking Gold Mount batteries.



Output Connectors:

| | |
|-------------|----------------|
| Model 9712D | D-Tap |
| Model 9712U | USB (5V, 1A) |
| Model 9712L | Lemo (2-pin) |
| Model 9712H | Hirose (4-pin) |
| Model 9712P | 2.1mm (PP90) |

Any connector can be used in any port.

SPECIFICATION

PAGlink Gold Mount PowerHub

Model No. 9712

Dimensions (H x W x D):

114 x 89 x 25mm (4.5" x 3.5" x 1.0").

Weight:

140g (5oz).

D-Tap Outputs:

Suitable for 12V camera accessories.
The output is unregulated.

USB Output:

Regulated at 5V (1 Amp).



PAG Ltd.
565 Kingston Road
London SW20 8SA
United Kingdom

E sales@paguk.com
T +44 (0)20 8543 3131
F +44 (0)20 8540 4116
www.paguk.com

© APR 2017 PAG Ltd. PAG is the trademark of PAG Ltd.
PAG reserves the right to change the specifications
contained herein without notice