

PAG CPA Camera Power Adaptor

Models 9701V & 9701

SAFETY INSTRUCTIONS

This leaflet contains important safety and operating instructions. Please read these fully and note all warnings before using the PAG Camera Power Adaptor.

Please follow all instructions and retain this leaflet for future reference.

The Camera Power Adaptor is not intended for any use other than the powering of video cameras from the PAG Cube Charger or the PAG V4-iPC charger.

IMPORTANT: Use only with the PAG Cube or V4-iPC chargers. Do not attempt to connect to any other power source.

Do not attempt to disassemble the Camera Power Adaptor. There are no user-serviceable parts inside, and incorrect reassembly may result in a safety hazard.

Do not use the Camera Power Adaptor if it has been damaged in any way. In this event you should seek advice from your nearest PAG Dealer, or direct from PAG Ltd. London, by telephoning +44 (0)20 8543 3131.

SPECIFICATION

PAG CPA Camera Power Adaptor

For use with specified PAG V-Mount chargers.
Model No. 9701V

PAG CPA Camera Power Adaptor

For use with specified PAGlok charger.
Model No. 9701

Input Connection:

To be powered only from PAG Cube chargers (Models 9702 & 9702V) or PAG V4-iPC charger (Model 9700V).

Output:

16.8V DC. Maximum current 5.5A (90W).

Output Connector:

XLR-4 (F) connector. Pin 1 Negative, Pin 4 Positive.

Overall Dimensions (H x W x D):

130mm x 86mm x 47mm
(5.1" x 3.4" x 1.85" approx.)

Weight:

190g (6.7oz. approx.)

OPERATING INSTRUCTIONS

IMPORTANT: Please ensure your camera can accept an input voltage of 16.8V without damage. Most newer cameras are designed for use with 14.4V / 14.8V Li-Ion batteries, and are likely to be suitable, but some older cameras could be damaged by the higher voltage. If suitability cannot be positively established, please do not connect your camera to the PAG CPA.

When the CPA is connected to a channel on the charger, the channel status will indicate CPA. This indicates the CPA has been identified by the charger. The charger will continue to charge any connected batteries until the CPA is activated.

To activate the CPA, press and hold the button on the CPA for one second. The 'Process Indicator' will move to the channel with the CPA, the CPA will then become active. The V4-iPC display will flash CPA, and the voltage on the display will be shown as 16.8. Charging will be suspended while the CPA is active.

To de-activate the CPA, press and hold the button for one second or remove the CPA from the V4-iPC. The charger will then resume charging any batteries connected.

The CPA is intended for use with specified PAG chargers only (see Specification). Use with other chargers may cause damage to the CPA or the camera.

SERVICING AND REPAIRS

Important: Refer all servicing or repairs to qualified servicing personnel. The PAG CPA contains electronics that do not require periodic maintenance, and consequently there are no user-serviceable parts inside.

Unqualified personnel should not attempt further investigation since this may

invalidate the guarantee and could cause more damage than the original fault. Seek advice from your nearest PAG dealer or direct from PAG Ltd., London, by telephoning +44 (0)20 8543 3131.

WARRANTY

Notwithstanding any provision of any agreement the following Warranty is exclusive: PAG Limited warrants each Camera Power Adaptor it manufactures to be free of defects in material and workmanship under use and service for **TWO YEARS** from the date of purchase. This warranty extends only to the original purchaser. This warranty shall not apply to parts which have been subject to misuse, neglect, accident or abnormal conditions of operation.

In the event of failure of a product covered by this warranty, PAG Limited will repair equipment returned to an authorised Service Facility within the period of the warranty, provided the warrantor's examination discloses to its satisfaction the product was defective. The warrantor may, at its option, replace the product in lieu of repair. With regard to any equipment returned within this period, said repairs or replacements will be made without charge. If the failure has been caused by misuse, neglect, accident or abnormal conditions of operation, repairs will be billed at a nominal cost. In such a case, an estimate will be submitted before work is started, if requested.

The foregoing Warranty is in lieu of all other warranties, express or implied, including but not limited to any implied warranty or merchantability, fitness or adequacy for any particular purpose or use. PAG Limited shall not be liable for any special, incidental, or consequential damages, whether in contract, tort, or otherwise.