



## PAG POWER PACKAGE FOR JVC HD100

PAGlok Power Adaptor, 2 PAGlok Batteries & PAG Freelancer Charger



**PAG** ™  
Professional Broadcast Equipment

**JVC**  
The Perfect Experience  
**ProHD**

*PAG's Power Package for the JVC GY-HD100 and optional Paglight M camera light.*

- The PAGlok Power Adaptor (Model 9522/75) has been developed to vastly extend the run-time of the JVC GY-HD100 camcorder by enabling the use of 12V to 14.8V professional PAGlok batteries. The unit incorporates a built-in DC Adaptor with a regulated 7.2V output to the camcorder.
- The PAGlok Connector incorporates a PP90 (2.1mm) output suitable for powering the 12V Paglight M, a hard-disk recorder, wireless receiver or any other 12V accessory that may be required.
- The weight of the PAGlok Power Adaptor and battery combined provides an excellent counterbalance to the JVC GY-HD100 lens.
- The PAG L95 Li-Ion battery is a 14.8V 6.5Ah 95 watt-hour power source that provides in excess of 5 hours run-time for the JVC GY-HD100. The battery's built-in Power & Time Display shows remaining run-time counting down in one minute increments, and battery capacity in both Ah and percentage. The quality of the PAG L95 is backed by United Nations certification and now carries a **2 year warranty**.
- The PAG Freelancer (Model 9613) is an ultra-compact, two-channel, fully-automatic, all-chemistry, sequential charger that can be powered from AC mains supplies worldwide.

**The following packages are available to suit a variety of requirements and budgets:**

<b>9522/75-P1</b>	PAGlok Power Adaptor, 9382 L95 Time Battery (95WH) x 2, 9613 Freelancer charger.	<b>£1050</b>
<b>9522/75-P2</b>	PAGlok Power Adaptor, 9335 L95 Power Circle Battery (95WH) x 2, 9613 Freelancer charger.	<b>£850</b>
<b>9522/75-P3</b>	PAGlok Power Adaptor, 9386 C50 Cobalt Battery (50WH) x 2, 9613 Freelancer charger.	<b>£650</b>

© 2005 PAG Ltd. PAG is the trademark of PAG Ltd.

PAG Ltd.  
565 Kingston Road  
Raynes Park  
London SW20 8SA

T +44 (0) 20 8543 3131  
F +44 (0) 20 8540 4797  
E email@paguk.com  
www.paguk.com

Sales Office  
T +44 (0) 20 8543 3131  
F +44 (0) 20 8540 4116  
E sales@paguk.com

**PAG** ™  
Professional Broadcast Equipment